

## **GSD-441 PG2**

PowerG Wireless Natural Gas (Methane) Detector



- Detects Methane CH4 gas used for cooking and heating
- Transmits alerts to the PowerMaster control panel and provides visual and audial alerts when gas is detected
- Self-test button for sensor, receiver, LED and buzzer checks
- Mute button to shut off triggered audial alarm
- Loud internal buzzer (85db)
- PowerG two-way Frequency Hopping Spread Spectrum FHSS-TDMA technology -Provides robustness and reliability closer than ever to wired
- Large transmission range enabling repeater-free installations
- Visible and transmitted low battery indication
- Meets EN 50194 requirements (the European standard for domestic gas alarms)

GSD-441 PG2 provides an early warning for leaks of natural gas (methane CH4) - the gas commonly used for cooking, home heating and water heating. GSD-441 PG2 transmits alerts to the PowerMaster® control panel which sounds the alarm and forwards the alert message to a central station or private phone number. This enables a rapid and effective response.

## **Specifications:**

**Power source:** 220-240V~ 50Hz

Back-up battery type: 3V CR123A

Lithium battery

Weight (including battery): 370g (13oz)

Operating temperature: 0°C to 45°C

(32°F to 113°F)

**Operating environment:** Indoor

**Dimensions:** 155 x 80 x 58mm

(6.1 x 3.1 x 2.3in)